

YO5

High Output Sounder



- Frequency of 400-2,850Hz - switchable
- 89 - 102 dBA at 1m
- Mains powered
- Activate via a Relay Module
- Indoor or outdoor use (IP65)

Description

The YO5 is a mains powered sounder for fire, security, and industrial applications. It connects to the alarm system via a relay base or module such as the Ei428 or the Ei128R. The sounder output is selectable from 400-2,850Hz with 32 different tones

ETIM Information

Suitable for wall mounting	True	Compatible with Google Assistant	False
Electricity consumption	0.08 A	Loudness	89 dB
Mounting method	Surface mounting	Compatible with Amazon Alexa	False
Type of current	AC	Housing colour	Red
Degree of protection (IP)	IP65	IFTTT support available	False
Suitable for ceiling mounting	True	Compatible with Apple HomeKit	False